

# LynxNet P2-L

SKU #950-LYNX-N-P2-L



The LynxNet P2-L is a network panic button that does not require a computer. Power can be PoE. Configuration is easy with the 12 VDC programming power supply (one per order) and a direct ethernet connection to a PC. Once configured the LynxNet P2-L can operate on an optional 12 VDC power supply or the built in PoE module. The Locking Hold Up Button (Size: 2.2" W x 2.5" L x 1.1" H) with Status LED and EOL resistor, connects with the 8 foot cord. When the button is activated, it instantly sends an alert to the LynxGuide server, allowing for any Lynx output device to be activated. The locking style require a staff member to test the button manually, so they can reset the button with the reset key, after the test press.

## Features and Benefits

- Enables a HUB (Hold Up Button) style locking panic button to be connected directly to your PoE network
- Requires a key to reset. Logs when alarm sends and when it is reset
- Supervised

### GENERAL SPECIFICATIONS:

**Width:** 3.1"

**Length:** 4.8"

**Height:** 1.2"

**Weight:** 1.5 Lbs.

**Power:** DC Power or PoE

**PS Input Voltage:** 100-240 VAC

**PS Output Voltage:** 12 VDC, 1.0 amp

**POE:** Class 1, 2.5W Max

**Supervision Interval:** 5 Minutes

### NETWORK SPECIFICATIONS

**RS-232:** For diagnostics and troubleshooting

**USB:** For diagnostics and troubleshooting

**Link LED:** Indicates network traffic

**Communication Protocol:** The LynxNet hardware and Lynx Client software achieves bidirectional communication through a client-initiated, persistent socket session to the LynxGuide server on ports 10117-10121. No network ingress connections are required. All server communications are TLS encrypted. In addition to providing security, this method is ideal if the hardware is behind a gateway, as no NAT rules are required to achieve connectivity.